Device driver routines (`leintr()`, `lerint()`, `leread()`, `leget()`) copy the received Ethernet packets from regions of the network interface buffer to *mbuf* chains. `Lerint()` first attaches a profile data buffer to a region of the network interface buffer and sets `svdevent`. That is, an event identifier for a packet is the address of the region. `Leread()` then copies the contents of the region to an *mbuf* chain by calling `leget()`. After copying, `leread()` detaches the profile data buffer from the region and re-attaches it to the *mbuf* chain. `Ethernet_input()` places the *mbuf* chain in the IP packet input queue and posts a software interrupt. This sequence is repeated until all Ethernet packets are processed. Then `interrupt()` restores the last value of `svdevent` and resumes normal execution.

When software interrupt is acknowledged, the network and transport layer routines (`ipintr()`, `udpinput()`, etc.) process *mbuf* chains to assemble, in this case, a UDP packet. `Ipintr()` sets `svdevent` when it removes an *mbuf* chain from the IP packet input queue. When `ipintr()` concatenates two *mbuf* chains, it merges the contents of the profile data buffer for the second *mbuf* chain into those for the first *mbuf* chain. This merging actually chains both the profile data buffers because of their structures (See Figure 4.4). Assembled packets are put into the receive queue of a socket and processes sleeping on that queue are woken up.

When the process waiting for the packet is resumed, it removes the packet from the receive queue of the socket. `Soreceive()` merges the contents of the profile data buffer attached to the packet into the profile data buffer of the running process pointed out by `svdproc`. In this way, resource consumption caused by processing of the packet is attributed to the process receiving the packet.

References

[1] S. L. Graham, P. B. Kessler and M. K. McKusick, "An Execution Profiler for Modular Programs", Software – Practice and Experience, Vol. 13, 671-685, (1983).

[2] S. L. Graham, P. B. Kessler and M. K. McKusick, "gprof: a Call Graph Execution Profiler", ACM SIGPLAN Notices 17(6), 120-126, (1982).

[3] R. J. Hall and A. J. Goldberg, "Call Path Profiling of Monotonic Program Resources in UNIX", 1993 Summer USENIX Technical Conference Proceedings, 1-13, (1993).

[4] M. K. McKusick, "Using gprof to Tune the 4.2BSD Kernel (May 21, 1984)", Distributed with 4.4BSD UNIX (1993).

[5] M. K. McKusick, "Measuring and Improving the Performance of Berkeley UNIX (DRAFT April 17, 1991)", Distributed with 4.4BSD UNIX, (1993).

[6] M. Loukides, *System Performance Tuning*, O'Reilly & Associates, Inc., (1990).

[7] A. Eustace and A. Srivastava, "ATOM A Flexible Interface for Building High Performance Program Analysis Tools", 1995 USENIX Technical Conference Proceedings, 303-314, (1995).

Author Information

Shingo Nishioka is a research scientist at the Advanced Research Laboratory, Hitachi, Ltd. His interests include programming languages and operating systems. He received his B.S., M.S., and Ph.D. degrees from Osaka University. He can be reached at nis@harl.hitachi.co.jp.

Atsuo Kawaguchi is a research scientist at the Advanced Research Laboratory, Hitachi, Ltd. His interests include file systems, memory management system, and microprocessor design. He earned his B.S., M.S., and Ph.D. degrees at Osaka University. He can be reached at atsuo@harl.hitachi.co.jp.

Hiroshi Motoda has been with Hitachi since 1967 and is currently a senior chief research scientist at the Advanced Research Laboratory and heads the AI group. His current research includes machine learning, knowledge acquisition, visual reasoning, information filtering, intelligent user interfaces, and AI-oriented computer architectures. He holds B.S., M.S., and Ph.D. degrees from the University of Tokyo. He was on the board of trustees of the Japan Society of Software Science and Technology and on the board of the Japanese Society for Artificial Intelligence. He was also on the editorial board of Knowledge Acquisition and on the editorial board of IEEE Expert. He can be reached at motoda@harl.hitachi.co.jp.

Alternately, all authors can be contacted via mail:

Advanced Research Laboratory, Hitachi, Ltd.
Hatoyama, Saitama, 350-03 Japan.

Availability

PKPROF and related documents are available at http://www.harl.hitachi.co.jp/~nis.